

5250/3270 Keyboard Map

for 38-Key MC3000

Booting Procedures

Boot Type	Procedure
Warm Boot	Selected via Start Menu
Cold Boot	Hold Power button for 15 Seconds

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Func><Ctrl>*<P>
Diagnostics	<Func><Ctrl>*<D>
Keyclicks On/Off	<Func><Ctrl>*<K>
Quiet Mode On/Off	<Func><Ctrl>*<Q>
Terminal Configuration	<Func><Ctrl>*<C>
Host Profiles	<Func><Ctrl>*<R>
Message Recall	<Func><Ctrl>*<M>
Free Cursor Mode	<Func><Ctrl>*<F>
Close Session	<Func><Ctrl>*<T>
Previous Session	<Ctrl><F9>
Next Session	<Ctrl><F10>
Caps Lock	N/A
View Mode On/Off	<Func><Ctrl>*<Z>
Scroll Left	<Ctrl><Left Arrow>
Scroll Right	<Ctrl><Right Arrow>
Scroll Up	<Ctrl><Up Arrow>
Scroll Down	<Ctrl><Down Arrow>

*Alpha Mode

5250/3270 Keyboard Map

for 38-Key MC3000

5250 Emulation Keys

5250 Key	Key Sequence
Attention	<Ctrl><7>
Backspace	<BKSP>
Back Tab	<Shift><Func><Right Arrow>
Clear	<Func><Ctrl><BKSP>
Delete	<Ctrl><BKSP>
Dup	<Ctrl><2>
Enter (Send)	<Ctrl><Enter>
Erase Input	<Ctrl><1>
Field Exit	<Enter>
Field Minus	<Ctrl>*<F>
Help	<Ctrl><4>
Home	<Ctrl><8>
Insert	<Ctrl><9>
Print	<Ctrl><.>
Reset	<Ctrl><,>
Roll Up	<Ctrl><6>
Roll Down	<Ctrl><3>
System Request	<Ctrl><5>
Tab	<Func><Right Arrow>
Left Arrow	<Left Arrow>
Right Arrow	<Right Arrow>
Up Arrow	<Up Arrow>
Down Arrow	<Down Arrow>

5250 Key	Key Sequence
F1	<F1>
F2	<F2>
F3	<F3>
F4	<F4>
F5	<F5>
F6	<F6>
F7	<F7>
F8	<F8>
F9	<F9>
F10	<F10>
F11	<Shift><F1>
F12	<Shift><F2>
F13	<Shift><F3>
F14	<Shift><F4>
F15	<Shift><F5>
F16	<Shift><F6>
F17	<Shift><F7>
F18	<Shift><F8>
F19	<Shift><F9>
F20	<Shift><F10>
F21	<Ctrl><F1>
F22	<Ctrl><F2>
F23	<Ctrl><F3>
F24	<Ctrl><F4>

*Alpha Mode

5250/3270 Keyboard Map

for 38-Key MC3000

3270 Emulation Keys

3270 Key	Key Sequence
Attention	<Ctrl><7>
Backspace	<BKSP>
Back Tab	<Shift><Func><Right Arrow>
Clear	<Esc>
Clear EOF	<Ctrl><0>
Delete	<Ctrl><BKSP>
Dup	<Ctrl><2>
Enter	<Enter>
Erase Input	<Ctrl><1>
Field Mark	<Ctrl>*<F>
Home	<Ctrl><8>
Insert	<Ctrl><9>
New Line	<Ctrl>*<P>
Reset	<Ctrl><, >
System Request	<Ctrl><5>
Tab	<Func><Right Arrow>
Left Arrow	<Left Arrow>
Right Arrow	<Right Arrow>
Up Arrow	<Up Arrow>
Down Arrow	<Down Arrow>
PA1	<Ctrl><F5>
PA2	<Ctrl><F6>
PA3	<Ctrl><F7>

3270 Key	Key Sequence
F1	<F1>
F2	<F2>
F3	<F3>
F4	<F4>
F5	<F5>
F6	<F6>
F7	<F7>
F8	<F8>
F9	<F9>
F10	<F10>
F11	<Shift><F1>
F12	<Shift><F2>
F13	<Shift><F3>
F14	<Shift><F4>
F15	<Shift><F5>
F16	<Shift><F6>
F17	<Shift><F7>
F18	<Shift><F8>
F19	<Shift><F9>
F20	<Shift><F10>
F21	<Ctrl><F1>
F22	<Ctrl><F2>
F23	<Ctrl><F3>
F24	<Ctrl><F4>

*Alpha Mode

5250/3270 Keyboard Map

for 38-Key MC3000

5250/3270 Character Map

Char	Key Sequence
Space	*<Space>
!	<Shift><1>
“	<Shift><Func><1>
#	<Shift><3>
\$	<Shift><4>
%	<Shift><5>
&	<Shift><7>
'	<Func><1>
(<Shift><9>
)	<Shift><0>
*	<Shift><8>
+	<Shift><Func><8>
,	<,>
-	<Func><7>
.	<.>
/	<Func><9>
0	<0>
1	<1>
2	<2>
3	<3>
4	<4>
5	<5>
6	<6>
7	<7>
8	<8>
9	<9>
:	<Shift><Func><6>
;	<Func><6>
<	<Shift><,>
=	<Func><8>
>	<Shift><.>
?	<Shift><Func><9>
@	<Shift><2>

*Alpha Mode

Char	Key Sequence
A	*<A>
B	*
C	*<C>
D	*<D>
E	*<E>
F	*<F>
G	*<G>
H	*<H>
I	*<I>
J	*<J>
K	*<K>
L	*<L>
M	*<M>
N	*<N>
O	*<O>
P	*<P>
Q	*<Q>
R	*<R>
S	*<S>
T	*<T>
U	*<U>
V	*<V>
W	*<W>
X	*<X>
Y	*<Y>
Z	*<Z>
[<Func><4>
\	<Func><3>
]	<Func><5>
^	<Shift><6>
_	<Shift><Func><7>
`	<Func><2>

Char	Key Sequence
a	<Shift>*<A>
b	<Shift>*
c	<Shift>*<C>
d	<Shift>*<D>
e	<Shift>*<E>
f	<Shift>*<F>
g	<Shift>*<G>
h	<Shift>*<H>
i	<Shift>*<I>
j	<Shift>*<J>
k	<Shift>*<K>
l	<Shift>*<L>
m	<Shift>*<M>
n	<Shift>*<N>
o	<Shift>*<O>
p	<Shift>*<P>
q	<Shift>*<Q>
r	<Shift>*<R>
s	<Shift>*<S>
t	<Shift>*<T>
u	<Shift>*<U>
v	<Shift>*<V>
w	<Shift>*<W>
x	<Shift>*<X>
y	<Shift>*<Y>
z	<Shift>*<Z>
{	<Shift><Func><4>
	<Shift><Func><3>
}	<Shift><Func><5>
~	<Shift><Func><2>
¢ ¹	N/A
¬ ¹	N/A
¹	N/A

¹ Only in 5250 mode.