

VT/HP Keyboard Map

for 28-Key MC3000

Booting Procedures

Boot Type	Procedure
Soft Reset	Selected via Start Menu
Hard Reset	Hold Power button for 15 Seconds

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Func><Ctrl>*<P>
Diagnostics	<Func><Ctrl>*<D>
Keyclicks On/Off	<Func><Ctrl>*<K>
Quiet Mode On/Off	<Func><Ctrl>*<Q>
Terminal Configuration	<Func><Ctrl>*<C>
Host Profiles	<Func><Ctrl>*<R>
VT/HP Terminal Setup	<Func><Ctrl>*<V>
Close Session	<Func><Ctrl>*<T>
Previous Session	<Ctrl><Left>
Next Session	<Ctrl><Right>
Caps Lock	N/A
View Mode On/Off	<Func><Ctrl>*<Z>
Scroll Left	<Func><Ctrl><Left>
Scroll Right	<Func><Ctrl><Right>
Scroll Up	<Func><Ctrl><Up>
Scroll Down	<Func><Ctrl><Down>

*Alpha Mode

VT/HP Keyboard Map

for 28-Key MC3000

VT-100 Emulation Keys

VT-100 Key	Key Sequence
Return	<Enter>
Backspace	<BKSP>
Tab	<Func><Right Arrow>
Up Arrow	<Up Arrow>
Left Arrow	<Left Arrow>
ESC	<Esc>
BS	<BKSP>
LF	<Ctrl><Enter>
Hard Terminal Reset	<Func><Ctrl>*<H>

VT-100 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)**	<Ctrl><BKSP>
Backtab	<Shift><Func><Right Arrow>
Down Arrow	<Down Arrow>
Right Arrow	<Right Arrow>
PF1	<Func><1>
PF2	<Func><2>
PF3	<Func><3>
PF4	<Func><4>

VT-220 Emulation Keys

VT-220 Key	Key Sequence
Return	<Enter>
Backspace	<BKSP>
Tab	<Func><Right Arrow>
Up Arrow	<Up Arrow>
Left Arrow	<Left Arrow>
Hard Terminal Reset	<Func><Ctrl>*<H>
Find	<Ctrl><5>
Insert Here	<Ctrl><9>
Prev Screen	<Shift><Down>
PF1	<Func><1>
PF2	<Func><2>
PF3	<Func><3>
PF4	<Func><4>
BREAK ¹	<Func><5>
F6	<Func><6>
F7	<Func><7>
F8	<Func><8>
F9	<Func><9>
F10	<Func><0>

VT-220 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)**	<Ctrl><BKSP>
Backtab	<Shift><Func><Right Arrow>
Down Arrow	<Down Arrow>
Right Arrow	<Right Arrow>
Soft Terminal Reset	<Func><Ctrl>*<S>
Select	<Ctrl><4>
Remove	<Shift><BKSP>
Next Screen	<Shift><Up>
F11	<Shift><Func><1>
F12	<Shift><Func><2>
F13	<Shift><Func><3>
F14	<Shift><Func><4>
F15/Help	<Shift><Func><5>
F16/Do	<Shift><Func><6>
F17	<Shift><Func><7>
F18	<Shift><Func><8>
F19	<Shift><Func><9>
F20	<Shift><Func><0>

*Alpha Mode

** See Wavelink Knowledge Base article #528

<http://www.wavelink.com/support.aspx>

¹ The BREAK key is currently not available.

VT/HP Keyboard Map

for 28-Key MC3000

HP Emulation Keys²

HP Key	Key Sequence
Return	<Enter>
Backspace	<BKSP>
Tab	<Func><Right Arrow>
Up Arrow	<Up Arrow>
Left Arrow	<Left Arrow>
Insert Line	<Ctrl><9>
Insert Char	<Shift><BKSP>
Hard Terminal Reset	<Func><Ctrl>*<H>
Prev	<Shift><Down>
Clear Line	<Shift><Func><3>
Insert Char with wrap	<Shift><Func><5>
Scroll Down	<Shift><Func><7>
F1	<Func><1>
F2	<Func><2>
F3	<Func><3>
F4	<Func><4>
User Key Menu	<Func><0>

*Alpha Mode

** See Wavelink Knowledge Base article #528

<http://www.wavelink.com/support.aspx>

HP Key	Key Sequence
Enter	<Enter>
Backspace(Delete)**	<Ctrl><BKSP>
Backtab	<Shift><Func><Right Arrow>
Down Arrow	<Down Arrow>
Right Arrow	<Right Arrow>
Delete Line	<Ctrl><5>
Delete Char	<Ctrl><4>
Soft Terminal Reset	<Func><Ctrl>*<S>
Next	<Shift><Up>
Clear Display	<Shift><Func><4>
Delete Char with wrap	<Shift><Func><6>
Scroll Up	<Shift><Func><8>
F5	<Func><5>
F6	<Func><6>
F7	<Func><7>
F8	<Func><8>
System Modes Menu	<Shift><Func><0>

² The BREAK and STOP keys are currently not available.

VT/HP Keyboard Map

for 28-Key MC3000

VT/HP Character Map

Char	Key Sequence
^@	<Ctrl><2>
^A	<Ctrl>*<A>
^B	<Ctrl>*
^C	<Ctrl>*<C>
^D	<Ctrl>*<D>
^E	<Ctrl>*<E>
^F	<Ctrl>*<F>
^G	<Ctrl>*<G>
^H	<Ctrl>*<H>
^I	<Ctrl>*<I>
^J	<Ctrl>*<J>
^K	<Ctrl>*<K>
^L	<Ctrl>*<L>
^M	<Ctrl>*<M>
^N	<Ctrl>*<N>
^O	<Ctrl>*<O>
^P	<Ctrl>*<P>
^Q	<Ctrl>*<Q>
^R	<Ctrl>*<R>
^S	<Ctrl>*<S>
^T	<Ctrl>*<T>
^U	<Ctrl>*<U>
^V	<Ctrl>*<V>
^W	<Ctrl>*<W>
^X	<Ctrl>*<X>
^Y	<Ctrl>*<Y>
^Z	<Ctrl>*<Z>
ESC	<Esc>
^\ ^] ^^ ^_	N/A
Space	<Space>
!	<Shift><1>
“	N/A
#	<Shift><3>
\$	<Shift><4>
%	<Shift><5>
&	<Shift><7>
'	N/A
(<Shift><9>
)	<Shift><0>
*	<Shift><8>

Char	Key Sequence
+	N/A
,	N/A
-	N/A
.	<.>
/	N/A
0	<0>
1	<1>
2	<2>
3	<3>
4	<4>
5	<5>
6	<6>
7	<7>
8	<8>
9	<9>
:	N/A
;	N/A
<	N/A
=	N/A
>	<Shift><.>
?	N/A
@	<Shift><2>
A	<Shift>*<A>
B	<Shift>*
C	<Shift>*<C>
D	<Shift>*<D>
E	<Shift>*<E>
F	<Shift>*<F>
G	<Shift>*<G>
H	<Shift>*<H>
I	<Shift>*<I>
J	<Shift>*<J>
K	<Shift>*<K>
L	<Shift>*<L>
M	<Shift>*<M>
N	<Shift>*<N>
O	<Shift>*<O>
P	<Shift>*<P>
Q	<Shift>*<Q>
R	<Shift>*<R>
S	<Shift>*<S>
T	<Shift>*<T>
U	<Shift>*<U>

Char	Key Sequence
V	<Shift>*<V>
W	<Shift>*<W>
X	<Shift>*<X>
Y	<Shift>*<Y>
Z	<Shift>*<Z>
[N/A
\	N/A
]	N/A
^	<Shift><6>
_	N/A
`	N/A
a	*<A>
b	*
c	*<C>
d	*<D>
e	*<E>
f	*<F>
g	*<G>
h	*<H>
I	*<I>
j	*<J>
k	*<K>
l	*<L>
m	*<M>
n	*<N>
o	*<O>
p	*<P>
q	*<Q>
r	*<R>
s	*<S>
t	*<T>
u	*<U>
v	*<V>
w	*<W>
x	*<X>
y	*<Y>
z	*<Z>
{	N/A
	N/A
}	N/A
~	N/A

* Alpha Mode