

Motorola MC75 Keyboard

Map

44-Key

Booting Procedures

Boot Type	Procedure
Warm Boot	Hold Power for 10 sec and release
Cold Boot	Power off device, Hold the 1 and 9 and press and release the power then release 1 and 9

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Alt><P>
Diagnostics	<Alt><D>
Keyclicks On/Off	<Alt><K>
Quiet Mode On/Off	<Alt><Q>
Terminal Configuration	<Alt><C>
Host Profiles	<Alt><R>
Message Recall	<Alt><M>
Free Cursor Mode	<Alt><F>
Close Session	<Alt><T>
VT/HP Terminal Setup	<Alt><V>
Previous Session	<Ctrl><Up>
Next Session	<Ctrl><Down>
Caps Lock	<Shift><Shift>
View Mode On/Off	<Alt><Z>
Scroll Left	<Alt><Orange><Up Arrow>
Scroll Right	<Alt><Orange><Down Arrow>
Scroll Up	<Alt><Up>
Scroll Down	<Alt><Down>

The left < - > has been mapped to Ctrl
The right < - > has been mapped to Alt

Motorola MC75 Keyboard Map

44-Key

5250 Emulation Keys

5250 Key	Key Sequence
Attention	<Ctrl><A>
Backspace	<Backspace>
Back Tab	<Shift><Tab>
Clear	<Ctrl><C>
Delete	<Shift><Space>
Dup	<Ctrl><Tab >
Enter	<Ctrl><Enter>
Erase Input	<Ctrl><E>
Field Exit	<Enter>
Field Minus	N/A
Help	<Ctrl><G>
Home	<Ctrl><*>
Insert	<Ctrl><. >
Print	<Ctrl><P>
Reset	<Ctrl><Space>
Roll Up	<Shift><Up>
Roll Down	<Shift><Down>
System Request	<Ctrl><S>
Tab	<Tab>
Left Arrow	<Orange><Up Arrow>
Right Arrow	<Orange><Down Arrow>
Up Arrow	<Up Arrow>
Down Arrow	<Down Arrow>

5250 Key	Key Sequence
F1	<Blue><1>
F2	<Blue><2>
F3	<Blue><3>
F4	<Blue><4>
F5	<Blue><5>
F6	<Blue><6>
F7	<Blue><7>
F8	<Blue><8>
F9	<Blue><9>
F10	<Blue><0>
F11	N/A
F12	N/A
F13	N/A
F14	N/A
F15	N/A
F16	N/A
F17	N/A
F18	N/A
F19	N/A
F20	N/A
F21	N/A
F22	N/A
F23	N/A
F24	N/A

The left < - > has been mapped to Ctrl
The right < - > has been mapped to Alt

Motorola MC75 Keyboard Map

44-Key

3270 Emulation Keys

3270 Key	Key Sequence
Attention	<Ctrl><A>
Backspace	<Backspace>
Back Tab	<Shift><Tab>
Clear	<Ctrl><Space>
Clear EOF	<Ctrl><O>
Delete	<Shift><Space>
Dup	<Ctrl><Tab >
Enter	<Enter>
Erase Input	<Ctrl><E>
Field Mark	<Ctrl><F>
Home	<Ctrl><*>
Insert	<Ctrl><.>
New Line	<Ctrl><N>
Reset	<Ctrl><R>
System Request	<Ctrl><S>
Tab	<Tab>
Left Arrow	<Orange><Up Arrow>
Right Arrow	<Orange><Down Arrow>
Up Arrow	<Up Arrow>
Down Arrow	<Down Arrow>
PA1	N/A
PA2	N/A
PA3	N/A

3270 Key	Key Sequence
F1	<Blue><1>
F2	<Blue><2>
F3	<Blue><3>
F4	<Blue><4>
F5	<Blue><5>
F6	<Blue><6>
F7	<Blue><7>
F8	<Blue><8>
F9	<Blue><9>
F10	<Blue><0>
F11	N/A
F12	N/A
F13	N/A
F14	N/A
F15	N/A
F16	N/A
F17	N/A
F18	N/A
F19	N/A
F20	N/A
F21	N/A
F22	N/A
F23	N/A
F24	N/A

WEB Emulation Keys

WEB Key	Key Sequence
Back	<Ctrl>
Forward	<Ctrl><F>
Home	<Ctrl><H>
Refresh	<Ctrl><R>
Stop	<Ctrl><S>

The left < - > has been mapped to Ctrl
The right < - > has been mapped to Alt

Motorola MC75 Keyboard Map

44-Key

VT-100 Emulation Keys

VT-100 Key	Key Sequence
Return	<Enter>
Backspace	<BackSpace>
Tab	<Tab>
Up Arrow	<Up Arrow>
Left Arrow	<Orange><Up Arrow>
ESC	<Ctrl><Space>
BS	<Backspace>
LF	<Ctrl><Enter>
Hard Terminal Reset	<Alt><H>

VT-100 Key	Key Sequence
Enter	<Enter>
Backspace(Delete) **	<Ctrl><BackSpace>
Backtab	<Shift><Tab>
Down Arrow	<Down Arrow>
Right Arrow	<Orange><Down Arrow>
PF1	<Blue><1>
PF2	<Blue><2>
PF3	<Blue><3>
PF4	<Blue><4>

VT-220 Emulation Keys

VT-220 Key	Key Sequence
Return	<Enter>
Backspace	<BackSpace>
Tab	<Tab>
Up Arrow	<Up Arrow>
Left Arrow	<Orange><Up Arrow>
Hard Terminal Reset	<Alt><H>
Find	<Ctrl><*>
Insert Here	<Ctrl><. >
Prev Screen	<Shift><Up>
PF1	<Blue><1>
PF2	<Blue><2>
PF3	<Blue><3>
PF4	<Blue><4>
BREAK ¹	<Blue><5>
F6	<Blue><6>
F7	<Blue><7>
F8	<Blue><8>
F9	<Blue><9>
F10	<Blue><0>

VT-220 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	<Ctrl><BackSpace>
Backtab	<Shift><Tab>
Down Arrow	<Down Arrow>
Right Arrow	<Orange><Down Arrow>
Soft Terminal Reset	<Alt><S>
Select	<Ctrl><Tab >
Remove	<Shift><Space>
Next Screen	<Shift><Down>
F11	N/A
F12	N/A
F13	N/A
F14	N/A
F15/Help	N/A
F16/Do	N/A
F17	N/A
F18	N/A
F19	N/A
F20	N/A

** See Wavelink Knowledge Base article #528

<http://www.wavelink.com/support.aspx>

The left < - > has been mapped to Ctrl
The right < - > has been mapped to Alt

Motorola MC75 Keyboard

Map

44-Key

HP Emulation Keys

HP Key	Key Sequence
Return	<Enter>
Backspace	<BackSpace>
Tab	<Tab>
Up Arrow	<Up Arrow>
Left Arrow	<Orange><Up Arrow>
Insert Line	<Ctrl><. >
Insert Char	<Shift><Space>
Hard Terminal Reset	<Alt><H>
Prev	<Shift><Up>
Clear Line	N/A
Insert Char with wrap	N/A
Scroll Down	N/A
F1	<Blue><1>
F2	<Blue><2>
F3	<Blue><3>
F4	<Blue><4>
User Key Menu	<Blue><0>

HP Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	<Ctrl><BackSpace>
Backtab	<Shift><Tab>
Down Arrow	<Down Arrow>
Right Arrow	<Orange><Down Arrow>
Delete Line	<Ctrl><*>
Delete Char	<Ctrl><Tab >
Soft Terminal Reset	<Alt><S>
Next	<Shift><Down>
Clear Display	N/A
Delete Char with wrap	N/A
Scroll Up	N/A
F5	<Blue><5>
F6	<Blue><6>
F7	<Blue><7>
F8	<Blue><8>
System Modes Menu	N/A

The left < - > has been mapped to Ctrl
The right < - > has been mapped to Alt

Motorola MC75 Keyboard

Map

44-Key

5250/3270/VT/HP Character Map

Char	Key Sequence
Space	<Space>
!	<Orange><N>
“	<Orange><O>
#	<Orange><A>
\$	N/A
%	<Orange><V>
&	<Orange>
'	<Orange><L>
(<Orange><G>
)	<Orange><H>
*	<Orange><Q>
+	<Orange><T>
,	<.>
-	<Orange><U>
.	<.>
/	<Orange><J>
0	<Orange><0>
1	<Orange><1>
2	<Orange><2>
3	<Orange><3>
4	<Orange><4>
5	<Orange><5>
6	<Orange><6>
7	<Orange><7>
8	<Orange><8>
9	<Orange><9>
:	<Orange><K>
;	N/A
<	<Shift><,>
=	<Orange><I>
>	<Shift><.>
?	<Orange><M>
@	<Orange><,>

Char	Key Sequence
A	<Shift><A>
B	< Shift >
C	< Shift ><C>
D	< Shift ><D>
E	< Shift ><E>
F	< Shift ><F>
G	< Shift ><G>
H	< Shift ><H>
I	< Shift ><I>
J	< Shift ><J>
K	< Shift ><K>
L	< Shift ><L>
M	< Shift ><M>
N	< Shift ><N>
O	< Shift ><O>
P	< Shift ><P>
Q	< Shift ><Q>
R	< Shift ><R>
S	< Shift ><S>
T	< Shift ><T>
U	< Shift ><U>
V	< Shift ><V>
W	< Shift ><W>
X	< Shift ><X>
Y	< Shift ><Y>
Z	< Shift ><Z>
[N/A
\	N/A
]	N/A
^	N/A
_	<Orange><Y>
`	N/A

Char	Key Sequence
a	<A>
b	
c	<C>
d	<D>
e	<E>
f	<F>
g	<G>
h	<H>
i	<I>
j	<J>
k	<K>
l	<L>
m	<M>
n	<N>
o	<O>
p	<P>
q	<Q>
r	<R>
s	<S>
t	<T>
u	<U>
v	<V>
w	<W>
x	<X>
y	<Y>
z	<Z>
{	N/A
	N/A
}	N/A
~	N/A

The left < - > has been mapped to Ctrl
The right < - > has been mapped to Alt