

VT/HP Keyboard Map

for 48-Key MC3000

Booting Procedures

Boot Type	Procedure
Soft Reset	Selected via Start Menu
Hard Reset	Hold Power button for 15 Seconds

Local Terminal Functions

Local Function	Key Sequence
Program Information	<Func><Ctrl><P>
Diagnostics	<Func><Ctrl><D>
Keyclicks On/Off	<Func><Ctrl><K>
Quiet Mode On/Off	<Func><Ctrl><Q>
Terminal Configuration	<Func><Ctrl><C>
Host Profiles	<Func><Ctrl><R>
VT/HP Terminal Setup	<Func><Ctrl><V>
Close Session	<Func><Ctrl><T>
Previous Session	*<Ctrl><Left>
Next Session	*<Ctrl><Right>
Caps Lock	N/A
View Mode On/Off	<Func><Ctrl><Z>
Scroll Left	*<Func><Ctrl><Left>
Scroll Right	*<Func><Ctrl><Right>
Scroll Up	*<Func><Ctrl><Up>
Scroll Down	*<Func><Ctrl><Down>

*Alpha Mode

VT/HP Keyboard Map

for 48-Key MC3000

VT-100 Emulation Keys

VT-100 Key	Key Sequence
Return	<Enter>
Backspace	<BKSP>
Tab	<Func><9>
Up Arrow	*<Up Arrow>
Left Arrow	*<Left Arrow>
ESC	<Func><7>
BS	<BKSP>
LF	<Ctrl><Enter>
Hard Terminal Reset	<Func><Ctrl><H>

VT-100 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)**	<Ctrl><BKSP>
Backtab	<Shift><Tab>
Down Arrow	*<Down Arrow>
Right Arrow	*<Right Arrow>
PF1	<Func><A>
PF2	<Func>
PF3	<Func><C>
PF4	<Func><D>

VT-220 Emulation Keys

VT-220 Key	Key Sequence
Return	<Enter>
Backspace	<BKSP>
Tab	<Func><9>
Up Arrow	*<Up Arrow>
Left Arrow	*<Left Arrow>
Hard Terminal Reset	<Func><Ctrl><H>
Find	<Ctrl><5>
Insert Here	<Ctrl><9>
Prev Screen	*<Shift><Down>
PF1	<Func><A>
PF2	<Func>
PF3	<Func><C>
PF4	<Func><D>
BREAK ¹	<Func><E>
F6	<Func><F>
F7	<Func><G>
F8	<Func><H>
F9	<Func><I>
F10	<Func><J>

VT-220 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)**	<Ctrl><BKSP>
Backtab	<Shift><Tab>
Down Arrow	*<Down Arrow>
Right Arrow	*<Right Arrow>
Soft Terminal Reset	<Func><Ctrl><S>
Select	<Ctrl><4>
Remove	<Shift><BKSP>
Next Screen	<Shift><Up>
F11	<Shift><Func><A>
F12	<Shift><Func>
F13	<Shift><Func><C>
F14	<Shift><Func><D>
F15/Help	<Shift><Func><E>
F16/Do	<Shift><Func><F>
F17	<Shift><Func><G>
F18	<Shift><Func><H>
F19	<Shift><Func><I>
F20	<Shift><Func><J>

*Alpha Mode

** See Wavelink Knowledge Base article #528

<http://www.wavelink.com/support.aspx>

¹ The BREAK key is currently not available.

VT/HP Keyboard Map

for 48-Key MC3000

HP Emulation Keys²

HP Key	Key Sequence
Return	<Enter>
Backspace	<BKSP>
Tab	<Func><9>
Up Arrow	*<Up Arrow>
Left Arrow	*<Left Arrow>
Insert Line	<Ctrl><9>
Insert Char	<Shift><BKSP>
Hard Terminal Reset	<Func><Ctrl><H>
Prev	*<Shift><Down>
Clear Line	<Shift><Func><C>
Insert Char with wrap	<Shift><Func><E>
Scroll Down	<Shift><Func><G>
F1	<Func><A>
F2	<Func>
F3	<Func><C>
F4	<Func><D>
User Key Menu	<Func><J>

HP Key	Key Sequence
Enter	<Enter>
Backspace(Delete)**	<Ctrl><BKSP>
Backtab	<Shift><Tab>
Down Arrow	*<Down Arrow>
Right Arrow	*<Right Arrow>
Delete Line	<Ctrl><5>
Delete Char	<Ctrl><4>
Soft Terminal Reset	<Func><Ctrl><S>
Next	*<Shift><Up Arrow>
Clear Display	<Shift><Func><D>
Delete Char with wrap	<Shift><Func><F>
Scroll Up	<Shift><Func><H>
F5	<Func><E>
F6	<Func><F>
F7	<Func><G>
F8	<Func><H>
System Modes Menu	<Shift><Func><J>

*Alpha Mode

** See Wavelink Knowledge Base article #528

<http://www.wavelink.com/support.aspx>

² The BREAK and STOP keys are currently not available.

VT/HP Keyboard Map

for 48-Key MC3000

VT/HP Character Map

Char	Key Sequence
^@	<Ctrl><2>
^A	<Ctrl><A>
^B	<Ctrl>
^C	<Ctrl><C>
^D	<Ctrl><D>
^E	<Ctrl><E>
^F	<Ctrl><F>
^G	<Ctrl><G>
^H	<Ctrl><H>
^I	<Ctrl><I>
^J	<Ctrl><J>
^K	<Ctrl><K>
^L	<Ctrl><L>
^M	<Ctrl><M>
^N	<Ctrl><N>
^O	<Ctrl><O>
^P	<Ctrl><P>
^Q	<Ctrl><Q>
^R	<Ctrl><R>
^S	<Ctrl><S>
^T	<Ctrl><T>
^U	<Ctrl><U>
^V	<Ctrl><V>
^W	<Ctrl><W>
^X	<Ctrl><X>
^Y	<Ctrl><Y>
^Z	<Ctrl><Z>
ESC	<Func><7>
^\ <^>	<Ctrl><Func><J>
^] <^>	<Ctrl><Func><L>
^^ <^>	<Ctrl><Func><P>
^_ <^>	<Ctrl><Func><K>
Space	<Func><BKSP>
!	<Shift><1>
“	<Shift><Func><X>
#	<Shift><3>
\$	<Shift><4>
%	<Shift><5>
&	<Shift><7>
'	<Func><X>
(<Shift><9>
)	<Shift><0>
*	<Shift><8>

Char	Key Sequence
+	<Shift><Func><P>
,	<Ctrl><Func><Q>
-	<Ctrl><Func><M>
.	<.>
/	<Func><Q>
0	<0>
1	<1>
2	<2>
3	<3>
4	<4>
5	<5>
6	<6>
7	<7>
8	<8>
9	<9>
:	<Shift><Func><V>
;	<Func><O>
<	<Ctrl><Func><.>
=	<Func><P>
>	<Shift><.>
?	<Shift><Func><Q>
@	<Shift><2>
A	<Shift><A>
B	<Shift>
C	<Shift><C>
D	<Shift><D>
E	<Shift><E>
F	<Shift><F>
G	<Shift><G>
H	<Shift><H>
I	<Shift><I>
J	<Shift><J>
K	<Shift><K>
L	<Shift><L>
M	<Shift><M>
N	<Shift><N>
O	<Shift><O>
P	<Shift><P>
Q	<Shift><Q>
R	<Shift><R>
S	<Shift><S>
T	<Shift><T>
U	<Shift><U>

Char	Key Sequence
V	<Shift><V>
W	<Shift><W>
X	<Shift><X>
Y	<Shift><Y>
Z	<Shift><Z>
[<Func><T>
\	<Shift><Func><O>
]	<Func><U>
^	<Shift><6>
_	<Shift><Func><K>
`	<Func><Y>
a	<A>
b	
c	<C>
d	<D>
e	<E>
f	<F>
g	<G>
h	<H>
I	<I>
j	<J>
k	<K>
l	<L>
m	<M>
n	<N>
o	<O>
p	<P>
q	<Q>
r	<R>
s	<S>
t	<T>
u	<U>
v	<V>
w	<W>
x	<X>
y	<Y>
z	<Z>
{	<Shift><Func><T>
	<Ctrl><Func><O>
}	<Shift><Func><U>
~	<Shift><Func><Y>