

VT/HP Keyboard Map

for 25-Key MC55

Booting Procedures

Boot Type	Procedure
Soft Reset	Hold Power for 7 Seconds
Hard Reset	Hold Power + 1 + 9

Local Terminal Functions

Local Function	Key Sequence
Program Information	N/A
Diagnostics	N/A
Keyclicks On/Off	N/A
Quiet Mode On/Off	N/A
Terminal Configuration	N/A
Host Profiles	N/A
VT/HP Terminal Setup	N/A
Close Session	N/A
Previous Session	<Orange> <Shift> <Up>
Next Session	<Orange> <Shift> <Down>
Caps Lock	N/A
View Mode On/Off	N/A
Scroll Left	<Orange> < Left>
Scroll Right	<Joystick> Right
Scroll Up	<Joystick> Up
Scroll Down	<Joystick> Down

*Alpha Mode

VT/HP Keyboard Map

for 25-Key MC55

VT-100 Emulation Keys

VT-100 Key	Key Sequence
Return	<Enter>
Backspace	<Backspace>
Tab	<Tab>
Up Arrow	<Up>
Left Arrow	<Orange> < Left>
ESC	<Blue> <#>
BS	<Backspace>
LF	N/A
Hard Terminal Reset	Hold Power +<1>+< 9>

VT-100 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	N/A
Backtab	N/A
Down Arrow	< Down >
Right Arrow	<Orange> <Right>
PF1	<Blue><1>
PF2	<Blue><2>
PF3	<Blue><3>
PF4	<Blue><4>

VT-220 Emulation Keys

VT-220 Key	Key Sequence
Return	<Enter>
Backspace	<Backspace>
Tab	<Tab>
Up Arrow	<Up>
Left Arrow	<Orange> < Left>
Hard Terminal Reset	Hold Power +<1>+< 9>
Find	N/A
Insert Here	N/A
Prev Screen	<Orange> <Shift> <Up>
PF1	<Blue><1>
PF2	<Blue><2>
PF3	<Blue><3>
PF4	<Blue><4>
BREAK ¹	<Blue><5>
F6	<Blue><6>
F7	<Blue><7>
F8	<Blue><8>
F9	<Blue><9>
F10	<Blue><0>

VT-220 Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	N/A
Backtab	N/A
Down Arrow	< Down >
Right Arrow	<Orange> <Right>
Soft Terminal Reset	Hold Power for 7 Seconds
Select	N/A
Remove	N/A
Next Screen	<Orange> <Shift> <Down>
F11	<Shift><Blue><1>
F12	<Shift><Blue><2>
F13	<Shift><Blue><3>
F14	<Shift><Blue><4>
F15/Help	<Shift><Blue><5>
F16/Do	<Shift><Blue><6>
F17	<Shift><Blue><7>
F18	<Shift><Blue><8>
F19	<Shift><Blue><9>
F20	<Shift><Blue><0>

*Alpha Mode

¹ The BREAK key is currently not available.

VT/HP Keyboard Map

for 25-Key MC55

HP Emulation Keys²

HP Key	Key Sequence
Return	<Enter>
Backspace	<Backspace>
Tab	<Tab>
Up Arrow	<Up>
Left Arrow	<Orange> <Left>
Insert Line	N/A
Insert Char	N/A
Hard Terminal Reset	N/A
Prev	<Orange> <Shift> <Up>
Clear Line	N/A
Insert Char with wrap	N/A
Scroll Down	N/A
F1	<Blue><1>
F2	<Blue><2>
F3	<Blue><3>
F4	<Blue><4>
User Key Menu	N/A

*Alpha Mode

HP Key	Key Sequence
Enter	<Enter>
Backspace(Delete)	N/A
Backtab	N/A
Down Arrow	<Down>
Right Arrow	<Orange> <Right>
Delete Line	N/A
Delete Char	N/A
Soft Terminal Reset	N/A
Next	<Orange> <Shift> <Up>
Clear Display	N/A
Delete Char with wrap	N/A
Scroll Up	N/A
F5	<Blue><5>
F6	<Blue><6>
F7	<Blue><7>
F8	<Blue><8>
System Modes Menu	N/A

² The BREAK and STOP keys are currently not available.

VT/HP Keyboard Map

for 25-Key MC55

VT/HP Character Map

Char	Key Sequence
^@	N/A
^A	N/A
^B	N/A
^C	N/A
^D	N/A
^E	N/A
^F	N/A
^G	N/A
^H	N/A
^I	N/A
^J	N/A
^K	N/A
^L	N/A
^M	N/A
^N	N/A
^O	N/A
^P	N/A
^Q	N/A
^R	N/A
^S	N/A
^T	N/A
^U	N/A
^V	N/A
^W	N/A
^X	N/A
^Y	N/A
^Z	N/A
ESC	N/A
^\ ^]	N/A
^^	N/A
^_ Space	<Space>
!	<Orange> <N>
“	<Orange> <O>
#	<Orange> <A>
\$	N/A
%	<Orange> <V>
&	<Orange>
'	<Orange> <L>
(<Orange> <G>
)	<Orange> <H>
*	<Orange> <Q>

Char	Key Sequence
+	<Orange><T>
,	<,>
-	<Orange> <U>
.	<.>
/	<Orange> <J>
0	<Orange> <Lightbulb>
1	<Orange> <W>
2	<Orange> <E>
3	<Orange> <R>
4	<Orange> <S>
5	<Orange> <D>
6	<Orange> <F>
7	<Orange> <Z>
8	<Orange> <X>
9	<Orange> <C>
:	<Orange> <K>
;	N/A
<	<Shift><,>
=	<Orange> <I>
>	<Shift><.>
?	<Orange> <M>
@	<Orange> <,>
A	<Shift> <A>
B	<Shift>
C	<Shift> <C>
D	<Shift> <D>
E	<Shift> <E>
F	<Shift> <F>
G	<Shift> <G>
H	<Shift> <H>
I	<Shift> <I>
J	<Shift> <J>
K	<Shift> <K>
L	<Shift> <L>
M	<Shift> <M>
N	<Shift> <N>
O	<Shift> <O>
P	<Shift> <P>
Q	<Shift> <Q>
R	<Shift> <R>
S	<Shift> <S>
T	<Shift> <T>
U	<Shift> <U>

Char	Key Sequence
V	<Shift> <V>
W	<Shift> <W>
X	<Shift> <X>
Y	<Shift> <Y>
Z	<Shift> <Z>
[N/A
\	N/A
]	N/A
^	N/A
=	<Orange> <Y>
`	N/A
a	<A>
b	
c	<C>
d	<D>
e	<E>
f	<F>
g	<G>
h	<H>
I	<I>
j	<J>
k	<K>
l	<L>
m	<M>
n	<N>
o	<O>
p	<P>
q	<Q>
r	<R>
s	<S>
t	<T>
u	<U>
v	<V>
w	<W>
x	<X>
y	<Y>
z	<Z>
{	N/A
	N/A
}	N/A
~	N/A

* Alpha Mode